

## **Specification**

# DUS<sup>\*</sup>hdgYW

Version: >Ubi Ufm201'

## **Table of Contents**

1. Product Specifications
1-1. Product Applicable2
1-2. Structure
1-3. Environmental Specifications2
1-4. Mechanical Characteristics2
1-5. Electrical Characteristics
2. Testing Conditions
2-1. Testing Conditions
2-2. Environmental Specifications
2-3. Mechanical Characteristics
2-4. Appearance
3. Reliability Condition
3-1. Temperature Condition4
4. Handling Notes
4. Handling Notes. 5   4-1. Precautions 5
4. Handling Notes. 5   4-1. Precautions 5   4-2. Handling Notes 5
4. Handling Notes. 5   4-1. Precautions. 5   4-2. Handling Notes. 5   4-3. Construction Notes 5
4. Handling Notes. 5   4-1. Precautions 5   4-2. Handling Notes. 5   4-3. Construction Notes 5   4-4. Electrical & Software Notice 5
4. Handling Notes.54-1. Precautions54-2. Handling Notes54-3. Construction Notes54-4. Electrical & Software Notice54-5. Mounting Notes6
4. Handling Notes. 5   4-1. Precautions 5   4-2. Handling Notes. 5   4-3. Construction Notes 5   4-4. Electrical & Software Notice 5   4-5. Mounting Notes 6   5. Warranty 9
4. Handling Notes. 5   4-1. Precautions. 5   4-2. Handling Notes. 5   4-3. Construction Notes. 5   4-4. Electrical & Software Notice 5   4-5. Mounting Notes 6   5. Warranty. 9   5-1. Warranty Period. 9
4. Handling Notes. 5   4-1. Precautions 5   4-2. Handling Notes. 5   4-3. Construction Notes 5   4-4. Electrical & Software Notice 5   4-5. Mounting Notes 6   5. Warranty 9   5-1. Warranty Period. 9   5-2. Warranty Target 9
4. Handling Notes. 5   4-1. Precautions 5   4-2. Handling Notes 5   4-3. Construction Notes 5   4-4. Electrical & Software Notice 5   4-5. Mounting Notes 6   5. Warranty 9   5-1. Warranty Period. 9   5-2. Warranty Target 9   5-3. Warranty Exceptions 9
4. Handling Notes. .5   4-1. Precautions. .5   4-2. Handling Notes. .5   4-3. Construction Notes .5   4-4. Electrical & Software Notice .5   4-5. Mounting Notes .6   5. Warranty .9   5-1. Warranty Period. .9   5-2. Warranty Target .9   5-3. Warranty Exceptions. .9   5-4. Tools .9
4. Handling Notes. 5   4-1. Precautions. 5   4-2. Handling Notes. 5   4-3. Construction Notes 5   4-4. Electrical & Software Notice 5   4-5. Mounting Notes 6   5. Warranty 9   5-1. Warranty Period. 9   5-2. Warranty Target 9   5-3. Warranty Exceptions. 9   5-4. Tools 9   5-5. Changes 9

## **Visual Inspection Criteria**

Up to 22" Size Exceed 22" Size

## **1. Product Specifications**

## 1-1. Product Applicable

§ This specification is applied to the Projected Capacitive DUS series.

## 1-2. Structure

§ For Dimensional and structural information, refer to the attached drawing.

## **1-3. Environmental Specifications**

Specification	Value		
Operating Temperature	-20°C to 70°C (no condensation)		
	-20°C to 60°C Less than 90%RH (no condensation)		
	Exceeding 60°C Less than 133.8g/m <sup>3</sup> (no condensation)		
Storage Temperature	-40°C to 75°C (no condensation)		
Storago Humidity	-40°C to 60°C Less than 95%RH (no condensation)		
Slorage Humidity	Exceeding 60°C Less than 142.9g/m <sup>3</sup> (no condensation)		
Chemical Resistance (top surface)	Toluene, Trichloroethylene, Acetone, Alcohol, Gasoline, Machine Oil, Ammonia, Glass Cleaner, Mayonnaise, Ketchup, Wine, Salad Oil, Vinegar, Lipstick, etc.		

## 1-4. Mechanical Characteristics

Specification	Value			
Operating Life	Input (finger) 50,000,000 hits			
Light Transmittance	91% (typical value at full wavelength)			
Surface Hardness	Over 5H (by JIS pencil hardness)			
Electrode Matrix Pitch	Approximately 5-7mm			

## **1-5. Electrical Characteristics**

Specification	Value
Maximum Voltage	DC6V
Recommended touch contact area	>=PHI 10mm

## 2. Testing Conditions

## 2-1. Testing Conditions

§ If the condition is not specified, the test is performed under the supplier's standard testing condition.

§ Tests are performed under the room temperature unless specified. The room temperature is regarded as follows:

Temperature: 20°C±5°C Humidity: 65%±10%RH

## 2-2. Environmental Specifications

§ Chemical Resistance Test

Condition: Tested after leaving the chemical on the surface for 12 hours then wiping it off by cloth. Judgement: Must be no effect in appearance.

## 2-3. Mechanical Characteristics

§ Operating Life Test	
-----------------------	--

Condition:	Testing rod: Refer to Figure 1		
	Load:	3N	
	Cycle:	2 hits/sec	
Judgement:	Must oper	ate properly after the test	



Figure 1. Testing rod 1

## 2-4. Appearance

§ Appearance Test

Condition: Tested by an examiner with over 1.0 eyesight at 30cm away from the product under the transmittable light at angle of over 60° to surface of the product.

Judgement: Must satisfy the specification.

## 3. Reliability Condition

## 3-1. Temperature Condition

§ Temperature Condition Test

Following test are performed in the condition with no dew condensation:

- Cold Test: Tested after leaving the parts in -40°C±3°C for 240 hours and in the room temperature for 2 hours.
- Heat Test: Tested after leaving the parts in 75°C±3°C for 240 hours and in the room temperature for 2 hours.
- Humidity Test: Tested after leaving the parts in the temperature 60°C±3°C, humidity 90 to 95% for 240 hours and in the room temperature for 2 hours.
- Cycle Test: Tested after 5 cycles of leaving the parts in the temperature  $-30^{\circ}C\pm3^{\circ}C$  for 1 hour and in the room temperature for 0.5 hours, then leaving the parts in the temperature  $70^{\circ}C\pm3^{\circ}C$  for 1 hour and in the room temperature for 0.5 hours.

Judgement: Must satisfy the following:

Function : Operate properly. Appearance: Must satisfy the specification.

## 4. Handling Notes

## 4-1. Precautions

§ This product is intended for use in standard applications (computers, office automation, and other office equipment, industrial, communications, and measurement equipment, personal and household devices, etc.) Please avoid using this product for special applications where failure or abnormal operation may directly affect human lives, or cause physical injury or property damage, or where extremely high levels of reliability are required (such as aerospace systems, vehicle operating control, atomic energy controls, medical devices for life support, etc.).

## 4-2. Handling Notes

- § Do not press or scratch the product with any object with a sharp edge or end.
- § Do not forcibly bend or fold the product.
- § When the product is stored, make sure it is packed in a packing box and stored in a storage temperature range, eliminating any outside load.
- § Do not use or store the product under a condition where the product will be exposed to water, organic solution or acid.
- § Do not use the product under the direct sunlight if a film material is used on it.
- § Do not disassemble the product.
- § When you handle the product, hold the product by its body. Do not hold by the tail.
- § Clean the product with a soft cloth or a soft cloth with neutral detergent or alcohol. When contaminated with chemicals, wipe them off immediately with caution not to cause injury to human body.
- § The edge of the glass is not rounded and may cause injury.

## 4-3. Construction Notes

- § The environmental specifications, mechanical characteristics, and electrical characteristics are only applied to the Active Area.
- § Do not use the touchscreen when the condensation occurs. The condensation inside of the touchscreen is a natural phenomenon and should disappear after the touchscreen is warmed up.

## 4-4. Electrical & Software Notice

Projected Capacitive Touchscreen was designed to work with our controller board.

If the driver software is to be developed by the customer, please study the characteristics of touch screen and controller before development.

#### 4-5. Mounting Notes

Projected capacitive touchscreen detects the touched locations by measuring the increased amount of the capacitance value between its electrodes at inputs. Once it is built into a system, capacitance couplings are continually yielded among the touchscreen, FPC tail, controller board and metal Chassis. When turned on, our projected capacitive touchscreen will automatically adjust its sensitivity level to the surrounding environment at the standby state in order to avoid the affects by the surrounding capacitance couplings. If surrounding environment changes or materials to alter the electrical field (a large capacitor, power-supply unit, LCD panel, or materials with high dielectric constant) is near, these external factors will adversely affect the function of the touch screen to detect the correct input positions.

At structure design, please refer to the mounting notes below and ensure enough gap distances among each component in order to avoid the external factors described above.

#### 4-5-1.Mounting

Fix the touchscreen firmly so that the gap distances between the touchscreen and other components will not be affected by touching or will not change with the passage of time. An unexpected input may be caused if the gap is too narrow.

The locations on which a certain gap distance is required are as follows.

- Between LCD panel and touchscreen: L1
- · Between touchscreen and the surface of the bezel: L4
- · Between touchscreen and the back of the bezel: L2
- Between tail and LCD panel, tail and metal chassis : L3 & L5 (an insulating tape can be used)

In case of using capacitive sensor outside, the moisture may cause the trouble.

#### 4-5-1-1. Mouting Toutchscreen on a display

It is recommended to use an insulating resin material for the bezel. Ensure the gap between the touchscreen and front bezel (L4)

If a metal plate is used for the bezel, unintended capacitance couplings may occur on the periphery of the active area. If a metal material is used for bezel, ensure the gap of approximately 2mm between touchscreen and bezel (L2).

In order to avoid the gap distance L1 from being changed with the passage of time, it is recommended to apply the adhesive tape onto all the 4 sides with no space (fully sealed) when gluing the touch screen.



4-5-1-2. Mounting touchscreen on back side of the bezel

It is recommended to use an insulating resin material for the bezel. Ensure the gap between the touchscreen and front bezel (L4).

If a metal plate is used for the bezel, unintended capacitance couplings may occur on the periphery of the active area.

If a metal plate or any other metallic materials is used for the bezel, ensure the gap distance of approximately 2mm between the touchscreen and bezel (L2).

Fix the touchscreen firmly so that the gap distance L1 will not be affected.



#### 4-5-1-3. Flat Surface Design

If the Flat Surface Design is preferred, please consult with us before proceeding. Thickness of cover glass and capacitance couplings at the periphery of the touchscreen must be considered for each individual case.



#### 4-5-2 Tolerance

There is a tolerance of 0.2 to 0.3mm for the dimensions of the touchscreen and tail. A gap must be made in the case and the connector to absorb the tolerance.



Fig.4-5-2

4-5-3.Tail

The tail must not be forcibly stressed or bent too hard. The conduction in the insulated area and wire breaking may be caused



## 5. Warranty

## 5-1. Warranty Period

- § The warranty period is limited to 1 year from the date of shipment. The warranty for the initial defects such as appearance defection is limited to 1 month.
- § Any defected parts under proper use will be examined by the supplier and replaced by the new parts if the defect is considered to be caused by the supplier.
- § The replacement is subject to be included in the next lot.

## 5-2. Warranty Target

- § The warranty only covers the product itself and does not cover any damage to others caused by using this product. Onsite repair or replacement is not supported.
- § We will do our best for delivery problem and product defect, but the warranty for the production line is not covered.
- § Capacitive touchscreens are structurally not repairable. All defected parts are subject to replacement.

#### 5-3. Warranty Exceptions

Following conditions are not covered with the warranty and subject to charge.

- § Any malfunctions and damages during transportation and transfer by the user.
- § Any malfunctions and damages caused by a natural disaster or a fire.
- § Any malfunctions and damages caused by static electricity
- § Any malfunctions and damages caused by the failure of the associated equipment.
- § If the product is remodeled, disassembled or repaired by the user.
- § If the product is glued onto the equipment and uninstalled.
- § Any malfunctions and damages caused by an improper usage and handling against the specifications and notes.

## 5-4. Tools

- § To maintain the quality, the printing screens and the die-cut plates are generally limited to use up to 1 year. Reorders after 1 year from the initial order or from the last renewal are subject to the tooling charge for replacing the printing screens and the die-cut plates. Reorders for the discontinued standard parts are also subject to tooling charge.
- § All the tools, such as CAD data (except for the drawing for approval), block copies (films), printing screens, and die-cut plates are not to be provided due to administrative reason.

## 5-5. Changes

- § Because of the manufacturing process, changing the dimensions, circuit pattern, and the tail position requires replacing most of the tools and is subject to high tooling charge. Please be careful when ordering and approving the drawing.
- § Circuit pattern and the materials that does not affect the environmental, electrical, and mechanical characteristics such as film, glass, ink and glue are subject to change for the supplier's reason or for improvement within the specifications.
- § Standard products are subject to change for improvement without notice.

## 6. Revision history

Rev 1.0(October 01, 2012) Initial release

Rev 1.1 (January 01, 2013)

Visual Inspection Criteria was added as a separate document.

Projected Capacitive Touchscreen DUS series Reference Rev. 1.1, January 30, 2013 ©2013 DMC Co., Ltd.

This document can be freely distributed, but any alternation to this document is prohibited.

## DMC Co., Ltd.

http://www.dmccoltd.com/english/ 11F Nisseki Takanawa Bldg., 2-18-10 Takanawa, Minato-ku, Tokyo 108-0074, Japan Phone: +81-3-6721-6731 (Japanese), 6736 (English) Fax: +81-3-6721-6732 1. Appearance Criteria (for viewing area with and without cover glass)

Item	W: Width W(mm) L:		Acceptable Number	Total	
		Length(mm)			
Liner	0.15≧W>0.1	5≧L	Up to 1pc per product		
(Foreign substance/scratch/	0.1≧W>0.08	15≧L	Up to 1 defect in		
transparent defects)			φ25mm		
Defects over 0.15mm in			including other kinds	$122 \leq 512e > 14$	
diameter will be judged in			of defects	Up to 10 delects	
circular.	0.08≧W	20≧L	Acceptable	per product	
Transparent defects mean					
bubble.				$[14 \leq \text{Size} > 10]$	
* e.g.:1 lint etc				Up to 7 defects per	
	0.7≧D>0.5		Up to 1 defect per	product	
Circulor			product		
	0.5≧D>0.3		Up to 1 defect in	$10 \leq 5120$	
(Foreign substance/scratch/			φ25mm	Up to 5 delects pe	
transparent defects)			including other kinds	product	
hubble list *1 etc			of defects		
	0.3≧D		Acceptable		
	D:average diame	]			
Dirt	No easily noticeable and no clear outline dirt should be OK				

\*1 Lint is the defect that is different transparent from other part due to the elevating surface by printing over foreign substance.

## 2. Chip (touch screen)

Site	Chips at areas other than electrode sections					
Judgment Criteria (for all sizes)	Chip at Corner		Tz Chip other than at corners			
	х	Y	Z	Х	Y	Z
	0.5≦X · Y≦2.0(mm) ≦t		$\leq 5.0(mm)$ 0.5 $\leq Y \leq 2.0(mm)$ $\leq t/2$			
	· · · · ·			Up to 8 defects per product, but each defects		
	Up to 2 de	efects per product		must be 20mm away from each other at each		
Acceptable					side.	
Numbers	X•Y<0.5mm is acceptable		Y<0.5mm is acceptable			
	But, if the chip re	eaches to Ag pattern	n, it is	But, if the chip reaches to Ag pattern, it is		
	unacceptable.			unacceptable.		

## 3. progressive Crack

Defect illustration	Judgment	
	NG	

## 4. Appearance criteria for color-printed area of covering glass (judged from surface view)

Item	Defect contents	Acceptable range	
Color Topo	Different color tone from original	Color Sample etc.	
	color		
Color Peeling	Color print coming off	Unaccep	otable
Color Lacking	Color print partly missing	Unaccep	table
Color Running	Ink bleed	The defect should not	be over edge face
Scratch	Scratch on color-printed part	Base glass should not be exposed	
	Color thickness is uneven	Should be no color un	evenness that can
Color Upovopposs		be easily detected.	
COIDI OTIEVEITITESS		(should not be detectab	
		– 6 seco	onds)
Pinhole through to the	D:average diameter =(longest+	Acceptable quantity	Total acceptable
base glass、	shortest diameters) / 2		quantity
Adhering foreign	0.3≧D>0.2	Up to 2 defects in	
substance which is	0.2≧D	φ30mm Up to 5 defects	
different color from the		Acceptable per product	
printing			
Tilt/Micalianmost	_	Should be within tolera	ances indicated by
riiviviisaligrimetti		the drav	wing

## 5. Chips and cracks on covering glass

Item	Defect contents	Acceptable range	
Crock	Progressive crack, chip: Refer to	Unacceptable	
CIACK	section 3		
	Chip (non-progressive crack) : Refer	Shorter than 3mm in length and	
	to section 2	narrower than 0.5mm in width: less	
		than 5 defects.	
Chip		The defect should not be recognizable	
		from the glass surface. Within	
		Y<0.2mm is acceptable. But the chip	
		should not be over the printing.	

Visual Inspection	Criteria	Туре	Pro-Cap
		Part No	Standard Model
			(Exceed 22" Size)
		File No	@083b

1. Appearance Criteria (for viewing area with and without cover glass)

Item	W: Width	L:	Acceptable Number	Total
	W(mm)	Length(mm)		TOLAT
Liner	0.15≧W>0.1	5≧L	Up to 2pc per product	
(Foreign substance/scratch/	0.1≧W>0.08	15≧L	Up to 1 defect in	
transparent defects)			φ25mm	
Defects over 0.15mm in			including other kinds of	
diameter will be judged in			defects	
circular.	0.08≧W	Acceptable	Acceptable	
Transparent defects mean				
bubble.				Lin to 15 defects
* e.g.:1 lint etc				Up to 15 delects
	1.0≧D>0.7		Up to 2 defect per	per product
Circular			product	
	0.7≧D>0.3		Up to 1 defect in	
			φ25mm	
Transparent defects			including other kinds of	
bubble, lint *1, etc			defects	
	0.3≧D		Acceptable	
	D:average diameter =(longest+shortest diameters) / 2			
Dirt	No easily noticeable and no clear outline dirt should be OK			

\*1 Lint is the defect that is different transparent from other part due to the elevating surface by printing over foreign substance.

2. Chip (touch screen)

Site	Chips at areas other than electrode sections					
Judgment Criteria (for all sizes)	Chip	p at Corner		Z Chip other than at corners		
	Х	Y	Z	х	Y	Z
	0.5≦X · Y	′≦2.0(mm)	≦t	≦5. 0(mm)	0.5≦Y≦2.0(mm)	≦t/2
Acceptable				Up to 15 d	efects per product, but	each
Numbers	Up to 2 defects per product			defects must be 20mm away from each other		
			at each side.			
	X·Y<0.5mm is acceptable But, if the chip		Y<0.5mm is acceptable But, if the chip			
	reaches to Ag pattern, it is unacceptable.		reaches to Ag pattern, it is unacceptable.			

## 3. progressive Crack

Defect illustration	Judgment
	NG

4. Appearance criteria for color-printed area of covering glass (judged from surface view)

Item	Defect contents	Acceptable	e range
Color Tone	Different color tone from original	Color Sam	ple etc.
	color		
Color Peeling	Color print coming off	Unaccep	otable
Color Lacking	Color print partly missing	Unaccep	otable
Color Running	Ink bleed	The defect should not	be over edge face
Scratch	Scratch on color-printed part	Base glass should	not be exposed
Color Unevenness	Color thickness is uneven	Should be no color un	evenness that can
		be easily d	etected.
		(should not be detect	able by gaze for 4
		- 6 seco	onds)
Pinhole through to the	D:average diameter =(longest+	Acceptable quantity	Total acceptable
base glass、	shortest diameters) / 2		quantity
Adhering foreign	0.3≧D>0.2	Up to 2 defects in	
substance which is		φ30mm	Up to 5 defects
different color from the			inφ30mm
printing	0.2≧D	Acceptable	
Tilt/Misalignment	_	Should be within toler	ances indicated by
		the drav	wing

5. Chips and cracks on covering glass

Item	Defect contents	Acceptable range	
Crack	Progressive crack, chip: Refer to	Unacceptable	
	section 3		
Chip	Chip (non-progressive crack) : Refer	Shorter than 3mm in length and	
	to section 2	narrower than 0.5mm in width: less	
		than 5 defects.	
		The defect should not be recognizable	
		from the glass surface. Within	
		Y<0.2mm is acceptable. But the chip	
		should not be over the printing.	





#### **DATA MODUL Headquarters Munich**

Landsberger Str. 322 D-80687 Munich - Germany Phone: +49-89-56017-0 Fax: +49-89-56017-119 www.data-modul.com

#### **Sales Office Hamburg**

Borsteler Chaussee 51 D-22453 Hamburg - Germany Phone: +49-40-42947377-0

## **Sales Office Duesseldorf**

Fritz-Vomfelde-Str. 8 D-40547 Duesseldorf - Germany Phone: +49-211-52709-0

## Sales Office Scandinavia

Lundsmindevej 5 DK-6000 Kolding - Denmark Phone: +45-75-224477

**DATA MODUL FRANCE** 7 rue Saint Christophe F-60300 BARON - FRANCE Phone: +33-3-44549699

DATA MODUL Italy, S.r.l.

Regus Center Senigallia Via Senigallia 18/2 I-20161 Milano - Italy Phone: +39-02-64672509

#### DATA MODUL Iberia, S.L.

c/ Adolfo Pérez Esquivel 3 Edificio Las Americas III Oficina 40 28230 Parque Empresarial Las Rozas / Madrid - Spain Phone: +34-916-366458

#### DATA MODUL Suisse GmbH

Stationsstr. 57 CH-8606 Nänikon - Switzerland Phone: +41-44-94091-50

#### DATA MODUL Ltd. / UK

Collins Building 3 Vigo Place - Aldridge - Walsall WS9 8UG - United Kingdom Phone: +44-1922-457358

#### DATA MODUL Inc. / USA

275 Marcus Blvd, Unit K Hauppauge, NY 11788 - USA Phone: +1-631-951-0800